

## Attenuation (dB per 100 feet)

Coax Cable Signal Loss (Attenuation) in dB per 100ft*								
Loss*	RG-174	RG-58	RG-8X	RG-213	RG-6	RG-11	RF-9914	RF-9913
1MHz	1.9dB	0.4dB	0.5dB	0.2dB	0.2dB	0.2dB	0.3dB	0.2dB
10MHz	3.3dB	1.4dB	1.0dB	0.6dB	0.6dB	0.4dB	0.5dB	0.4dB
50MHz	6.6dB	3.3dB	2.5dB	1.6dB	1.4dB	1.0dB	1.1dB	0.9dB
100MHz	8.9dB	4.9dB	3.6dB	2.2dB	2.0dB	1.6dB	1.5dB	1.4dB
200MHz	11.9dB	7.3dB	5.4dB	3.3dB	2.8dB	2.3dB	2.0dB	1.8dB
400MHz	17.3 B	11.2dB	7.9dB	4.8dB	4.3dB	3.5dB	2.9dB	2.6dB
700MHz	26.0dB	16.9dB	11.0dB	6.6dB	5.6dB	4.7dB	3.8dB	3.6dB
900MHz	27.9 B	20.1dB	12.6dB	7.7dB	6.0dB	5.4dB	4.9dB	4.2dB
1GHz	32.0dB	21.5dB	13.5dB	8.3dB	6.1dB	5.6dB	5.3dB	4.5dB
Imped	50ohm	50ohm	50ohm	50ohm	75ohm	75ohm	50ohm	50ohm
<p>* <b>Note:</b> Coax losses shown above are for 100 feet lengths. Loss is a length multiplier, so a 200 ft length would have twice the loss shown above and a 50 ft length would have half the loss. This multiplier factor is why you should keep cable installation lengths between radios and antennas as short as practical!</p>								

	LMR-1200	LMR-900	LMR-600	1/2" Superflex	LMR-400	Belden 9913F7	9914	RG214 RG213	LMR-240	Belden RG8X	LMR-200	LMR-195	RG-58/U
Frequency/Size	1.200"	0.870"	0.590"	0.520"	0.405"	0.405"	0.400"	0.405"	0.240"	0.242"	0.195"	0.195"	0.195"
30 MHz	0.209	0.288	0.421	0.561	0.7	0.8	0.8	1.2	1.3	2.0	1.8	1.8	2.5
50 MHz	0.272	0.374	0.547	0.730	0.9	1.1	1.1	1.6	1.7	2.5	2.3	2.3	3.1
150 MHz	0.481	0.658	0.964	1.29	1.5	1.7	1.7	2.8	3.0	4.7	3.9	4.0	6.2
220 MHz	0.589	0.803	1.18	1.58	1.8	2.1	2.1	3.5	3.7	6.0	4.8	4.8	7.4
450 MHz	0.864	1.17	1.72	2.32	2.7	3.1	3.1	5.2	5.3	8.6	6.9	7.0	10.6
900 MHz	1.27	1.70	2.50	3.41	3.9	4.4	4.5	8.0	7.6	12.8	9.9	9.9	16.5
1,500 MHz	1.69	2.24	3.31	4.57	5.1	6.0			9.9		12.7	12.9	

## Attenuation of Coaxial Transmission Lines in the VHF/UHF/Microwave Amateur and ISM Bands

Cable Type	144 MHz	220 MHz	450 MHz	915 MHz	1.2 GHz	2.4 GHz	5.8 GHz
RG-58	6.2	7.4	10.6	16.5	21.1	32.2	51.6
	(20.3)	(24.3)	(34.8)	(54.1)	(69.2)	(105.6)	(169.2)
	4.7	6.0	8.6	12.8	15.9	23.1	40.9

<b>RG-8X</b>	(15.4)	(19.7)	(28.2)	(42.0)	(52.8)	(75.8)	(134.2)
<b>LMR-240</b>	3.0 (9.8)	3.7 (12.1)	5.3 (17.4)	7.6 (24.9)	9.2 (30.2)	12.9 (42.3)	20.4 (66.9)
<b>RG-213/214</b>	2.8 (9.2)	3.5 (11.5)	5.2 (17.1)	8.0 (26.2)	10.1 (33.1)	15.2 (49.9)	28.6 (93.8)
<b>9913</b>	1.6 (5.2)	1.9 (6.2)	2.8 (9.2)	4.2 (13.8)	5.2 (17.1)	7.7 (25.3)	13.8 (45.3)
<b>LMR-400</b>	1.5 (4.9)	1.8 (5.9)	2.7 (8.9)	3.9 (12.8)	4.8 (15.7)	6.8 (22.3)	10.8 (35.4)
<b>3/8" LDF</b>	1.3 (4.3)	1.6 (5.2)	2.3 (7.5)	3.4 (11.2)	4.2 (13.8)	5.9 (19.4)	8.1 (26.6)
<b>LMR-600</b>	0.96 (3.1)	1.2 (3.9)	1.7 (5.6)	2.5 (8.2)	3.1 (10.2)	4.4 (14.4)	7.3 (23.9)
<b>1/2" LDF</b>	0.85 (2.8)	1.1 (3.6)	1.5 (4.9)	2.2 (7.2)	2.7 (8.9)	3.9 (12.8)	6.6 (21.6)
<b>7/8" LDF</b>	0.46 (1.5)	0.56 (2.1)	0.83 (2.7)	1.2 (3.9)	1.5 (4.9)	2.3 (7.5)	3.8 (12.5)
<b>1 1/4" LDF</b>	0.34 (1.1)	0.42 (1.4)	0.62 (2.0)	0.91 (3.0)	1.1 (3.6)	1.7 (5.6)	2.8 (9.2)
<b>1 5/8" LDF</b>	0.28 (0.92)	0.35 (1.1)	0.52 (1.7)	0.77 (2.5)	0.96 (3.1)	1.4 (4.6)	2.5 (8.2)

**Attenuation of Various Transmission Lines in Amateur and ISM Bands in dB/ 100 ft (dB/ 100 m)**